

## **CODE A48 - 48 CHANNELS**

### **Lighting Console for dimmer control**

The CODE A48 Series consoles offer output digital DMX512/1990. Any dimmer using this protocol can be controlled by these consoles.

CODE consoles allow to record scenes, edit chase programs and use internal chases. They have the ability to run one manual scene simultaneously.



## **MODELOS**

### **A48**

- 48 DMX channels with optical isolated output.
- LCD display
- 24 channel faders. 12 submasters faders x 3 pages, 1 chase speed fader, 1 chase cross fader, 1 channel master fader and 1 mater fader.
- 36 submaster faders for edit and store.
- 24 chases, at most 80 steps each.
- Music trigger function for Chase.
- 1 manual scene, 12 submaster scenes and 1 chase can operate simultaneously.
- Flash control: Channel, Submaster, Master.
- The data auto-saves.
- Power supply: AC100-240V, 50-60Hz.
- Size: 482mmx310mmx95mm.
- Net weight: 7kg approx.

