



PARTY 500 CONSOLE

LIGHTING CONTROL CONSOLE

512 DMX Channels with 2 DMX optical isolated output.

- Maximum 80 Units for patching all kinds of Fixtures.
- Fixtures within 40 channels are available.
- LCD display in Chinese/English.
- Three Optical Encoders, offer smooth operation and long life.
- Up to 50 Playbacks, controlled by 10 Playback fadersx5 pages.
- Up to 100 groups.
- Freely-editing 40 Presets, including various color, gobos and position, are controlled by 10 Preset buttonsx4 pages.
- Effect Generator provides circle, square, polygon, rainbow and other Effects.
- Over 8000 fixtures in System Library, with create and edit function of User Library, a new fixture can be created easily.
- Freely download fixtures Lib and firmware updated version.
- USB backup system enable user to backup the show in a file.
- Music trigger function for Chase of Playback.
- Can be controlled by MIDI Master. Party 600 can be connected by MIDI signal, one for master, another for slave.
- The Data auto-saves.
- Option: 12V auxiliary light.
- Power supply: AC100-240V, 50-60Hz.
- Size: 482mmx355mmx98mm.
- Net weight: 7kg approx.

MODELOS

PARTY 500

